



BY-M4C

Cardioid Lavalier Microphone

Cardioid Polar Pattern

The lavalier mic with the cardioid pattern yields a generous pickup area while maintaining adequate feedback and noise rejection at the off-axis section of the capsule.

Specification:

Type Electret	Condenser Microphone
Frequency Response	35-18KHz +/-3dB
Maximum Sound Input Level	120 dB
Sensitivity	-38dB +/-3dB / 0dB=1V/Pa, 1kHz
Output Impedance	200 ohms
Power Requirement	48V Phantom Power
Signal-to-Noise Ratio	78 dB
Accessories	Windscreen, Lapel clip



BY-M4C

心型电容式领夹麦

感谢您选择BOYA!

BY-M4C是一款心型电容式领夹麦，清晰收录正前方的音源，并有效隔绝两侧及后方的噪音。

参数

类型	电容式麦克风
频率响应	35-18KHz +/-3dB
最大声压级	120dB
灵敏度	-38dB +/-3dB / 0dB=1V/Pa,1kHz
输出阻抗	200 ohms
供电方式	48V幻象电源供电
信噪比	78dB
附件	防风毛/领夹

www.boya-mic.com

SHENZHEN JIAYZ PHOTO INDUSTRIAL., LTD.

The BOYA logo is a trademark which is registered and owned by Shenzhen Jiayz Photo Industrial., Ltd.

深圳市长丰影像器材有限公司

地址:广东省深圳市龙华区观澜街道大富社区硅谷动力智能终端产业园A16栋

TEL: 400 6131096

Email: sales@boya-mic.com

www.boya-mic.com / www.jiayz.com